



Quality and reliability is our tradition

KYORITSU JAPAN

www.kew-ltd.co.jp

www.kyoritsu-instrumenti.com

www.melcobuda.co.yu

◀ Diferencijalna merna kljesta

MODEL **2432**

- Model visoke osetljivosti merenja Model
- Frekvencijski prekidač da eliminiše efekte harmonika.
- Tri AC strujna opsega :
4mA/40mA/100A
- Data hold funkcija.
- Pik hold funkcija.
- Sleep funkcija za stiti baterije.
- Dizajniran po međunarodnom sigurnosnom standardu IEC61010-1 CAT.III 300V

Φ40	MAX AC100A	Resolution 0.001mA	Filter
PEAK 10ms			



CE

AC A (50/60Hz)	4/40mA/100A ±1%rdg±5dgt (4/40mA) ±1%rdg±5dgt (0~80A) ±5%rdg (80.1~100A)
AC A (WIDE)	4/40mA/100A ±1%rdg±5dgt [50/60Hz], ±2.5%rdg±10dgt [20Hz~1kHz] (4/40mA) ±1%rdg±5dgt [50/60Hz], ±2.5%rdg±10dgt [40Hz~1kHz] (0~80A) ±5%rdg [50/60Hz], ±10%rdg [40Hz~1kHz] (80.1~100A)
Frekvencijski opseg	20Hz~1kHz (40Hz~1kHz:100A)
Maximalni napon kola	600V AC/DC (izmedju linije/neutralne) 300V AC/DC (prema zemlji)
Max mereni kabal	Ø40mm max.
Sigurnosni Standard	IEC61010-1 CAT.III 300V Pollution Degree 2 IEC61010-2-032
Efekt spoljnog Magnetnog polja	2mA AC priblizno prilaskom do 15mm-Fi kabela zaštite 100A AC
Max naponsko preopterećenje	3700V AC do 1 minute

Vreme odgovra	oko. 2 secunde
Napajanje	Dve R03 ili ekvivalentne (DC1.5V) baterije
Dimenzije	185(L) × 81(W) × 32(D)mm
Tezina	290g approx.
Dodatci	9052(Carrying Case) R03(1.5V) × 2 Instruction Manual
Posebno se narucujul	8004/8008 (Multi-Tran)*

* Multi tran se koristi samo za merenje standardnih struja ne I stetnih