



Quality and reliability is our tradition

KYORITSU JAPAN

www.kew-ltd.co.jp

www.melcobuda.co.yu

◀ Digitalni Multimetar

KEW

1018 (meko kuciste tip) / 1018H (tvrdo kuciste tip)

- Prikazuje : 4000 brojeva.
- Automatsko menjanje opsega.
- Diode test .
- Kapacitet test .
- Kontinuitet test.
- Automatsko gasenje posel 15 minuta nekoriscenja ,radi stednje baterija.
- Dizajniran po medjunarodnom sigurnosnom standardu IEC61010-1 CAT.III 300V.

NOVO

Kuciste je od Sceleton plastike koja je poslednja rec tehnologije !!!

■ Tvrdo kuciste tip

■ Meko kuciste tip



CE

DC V	400mV/4/40/400/600V(Input Impedance 10MΩ) ±0.8%rdg±5dgt(400mV/4/40/400V) ±1.0%rdg±5dgt(600V)
AC V	4/40/400/600V(Input Impedance 10MΩ) ±1.3%rdg±5dgt(4/40V) ±1.6%rdg±5dgt(400/600V)
Hz	10/100Hz/1/10/100/200kHz
Ω	400Ω/4/40/400kΩ/4/40MΩ ±1.0%rdg±5dgt(400Ω/4/40/400kΩ/4MΩ) ±2.5%rdg±5dgt(40MΩ)
Diode Test	4V Release Voltage:Approx. 0.4mA Test struja
Kapacitet Test	4nF/40nF/400nF/4μF/40μF/200μF
Continuity zvuk -biper	400Ω(Buzzer zvuk se ukuljujuje ispod 120Ω)
Maksimalmo opterecenje	3700V AC for 1 minute
Standard	IEC 61010-1 CAT.III 300V

	IEC 61010-2-031 IEC 61326-1
Napajanje	LR44(1.5V) × 2
Dimenzije	107(L) × 54(W) × 10(D)mm
Tezina	70g approx.
Dodatci	LR44× 2 baterije Instruction Manual 1018(Soft Case) ili 1018H(Hard Case)